



Product information sheet

AXBUCH-MI6V Mitsubishi Backup Camera Retain/Add-On 2014-Up

INTERFACE FEATURES

- Retains the factory backup camera to an aftermarket radio
- Allows an aftermarket camera to be added to the factory screen
- Includes the AXCS-6V 12-volt to 6-volt converter

APPLICATIONS

MITSUBISHI

Lancer	2014-Up	Outlander	2014-Up
Lancer Sportback	2014-Up	Outlander Sport	2014-Up

INTERFACE COMPONENTS

- AXBUCH-MI6V-6V harness • AXCS-6V 12-volt to 6-volt converter

TOOLS REQUIRED

- Wire cutter • Crimping tool • Solder gun • Tape
- Connectors (example: butt connectors, bell caps, etc.)

Connections to be made

The AXBUCH-MI6V-6V can be connected two different ways

To retain the factory backup camera to an aftermarket radio:

- Connect the **Black** wire to chassis ground, and also to the **Black** wire of the AXCS-6V.
- Connect the **Yellow** wire to battery power.
- Connect the **Red** wire to the **Blue/Red** wire of the AXCS-6V.
- Connect the **Green/Purple** wire to the reverse wire of the aftermarket radio, and also to the **Blue/White** wire of the AXCS-6V.
- Connect the *male* **Yellow** RCA jack to the rear camera input of the aftermarket radio.

To allow an aftermarket camera to be added to the OEM screen:

- Connect the **Black** wire to the ground wire of the aftermarket camera.
- Connect the **Yellow** wire to battery wire of the aftermarket camera.
- Connect the *female* **Yellow** RCA jack to the aftermarket camera.
- The AXCS-6V 12-volt to 6-volt converter will not be used in this application.